



PL2 MK3 V2



20mA Telemetry Pacer and Filter



Application Notes

The PL2 is designed to filter 20mA telemetry commands when used with RF and fibre links. The unit provides additional error checking and also has the option of filtering out unwanted commands.

Features

- Dipswitch selectable input, compatible with both RS232 and 20mA loop
- Supplied with all necessary cables and connections
- Full range of diagnostic LEDs displaying input and output activity as well as power and processor status
- Autopan, random pan, preset, patrols and dome menu displays can all be disabled / enabled
- Dipswitch configurable for matrix monitor output
- Dipswitch selectable filter to eradicate spurious commands

Product includes

1 x PL2 in plastic enclosure
1 x SA-PL64-3 moulded DB9F to DB9M cable
1 x 98005 Mk 2 (20mA RS232 converter) and installation sheet
1 x DB9F connector
1 x DB9 blue hood
Installation instructions



Building Block Video Ltd.

17 Apex Park, Diplocks Way, Hailsham, East Sussex, UK BN27 3JU
Tel: +44 (0) 1323 842727 Support: +44 (0) 1323 444600
Fax: +44 (0) 1323 842728 Web Site: www.bbvctv.com



PL2 MK3 V2



20mA Telemetry Pacer and Filter

Technical specification

Power supply	9Vdc 500mA
Inputs	1 x BBV 20mA input
Outputs	1 x BBV 20mA output
Features	9-way male D-type chassis mounted socket for RS232 input/output Fully dipswitch programmable for ease of installation 3 diagnostic LEDs to simplify problem shooting
Installation	Supplied with required connectors and Cable.
Dimensions	Width 208mm Depth 83mm Height 35mm
Weight	0.7Kg
Colour	RAL9002



Building Block Video Ltd.

17 Apex Park, Diplocks Way, Hailsham, East Sussex, UK BN27 3JU
Tel: +44 (0) 1323 842727 Support: +44 (0) 1323 444600
Fax: +44 (0) 1323 842728 Web Site: www.bbvctv.com